FOYDALANISH QO‘LLANMASI

2 kanalli Zigbee kalit moduli

QS-Zigbee-S10-2C

Zigbee 3.0 • CE • RoHS



Zigbee CE • RoHS

TEXNIK XUSUSIYATLAR

Mahsulot turi: 2 kanalli Zigbee kalit moduli

Kuchlanish: AC 100–240 V, 50/60 Hz

LED yuklama: 2 × 250 W; 2 × 10 A

Chastota: 2.4 GHz, IEEE 802.15.4

Protokol: Zigbee 3.0

Ish haroratı: −10…+40 °C

O‘lcham: 39.2 × 39.2 × 18 mm

Himoya darajasi: IP20




MASOFADAN VA MAHALLIY BOSHQARUV

Tuya Smart ilovasi va mos Zigbee shlyuzi yordamida boshqarish.

Taymer, ovozli boshqaruv va qurilmaga umumiy kirish funksiyalari mavjud bo‘lishi mumkin.





O‘RNATISH BO‘YICHA OGOHLANTIRISH

Elektr tarmog‘iga o‘rnatishni faqat malakali elektrik amalga oshirishi kerak.

Qurilmani bolalardan uzoqda saqlang.

Nam joyda yoki kuchli issiqlik yaqinida ishlatmang.

Qurilmani o‘zboshimchalik bilan qismlarga ajratmang va ta’mirlamang.

QO‘LDA BOSHQARISH

Savol 1. Modul ilovaga ulanmasa nima qilish kerak?

Parol va Zigbee shlyuzi holatini tekshiring. Modul ulanish rejimida ekaniga ishonch hosil qiling.

Oddiy devor kaliti orqali boshqarish ulanish sxemasiga bog‘liq.

KO‘P SO‘RALADIGAN SAVOLLAR

Savol 2. Qanday jihozlar ulanadi?

Mos keladigan yoritish va boshqa maishiy elektr yuklamalari. Ruxsat etilgan quvvatdan oshirmang.

Savol 3. Wi-Fi o‘chsa nima bo‘ladi?

Masofadan boshqarish ishlamasligi mumkin; mahalliy boshqarish ulanishga bog‘liq.

KO‘P SO‘RALADIGAN SAVOLLAR

Savol 4. Tarmoq yoki parol o‘zgarsa nima qilish kerak?

Shlyuzni yangi tarmoqqa ulang va zarur bo‘lsa modulni qayta qo‘shing.

Savol 5. Qurilma qanday tiklanadi?

Reset tugmasini taxminan 10 soniya bosib turing. Indikator tez miltillashini tekshiring.

ULANISH SXEMALARI

Bir kalit bilan, ikki kalit bilan yoki tashqi kalitsiz ishlash

ILOVA UCHUN QO‘LLANMA

1. Tuya Smart ilovasini yuklab oling.

QR-kodni skanerlang yoki App Store / Google Play orqali ilovani qidiring.

IOS APP / Android APP

1 ican the QR code to download Tuya

HISOB YARATISH

2. Ilovaga telefon raqaminigiz yoki elektron pochtangiz orqali kiring.

Tasdiqlash kodini kiriting va hisobingizni sozlang.



your account with
ber or e-mail
e verification code
sword.

ZIGBEE SHLYUZI

3. Zigbee shlyuzi (gateway) ilovaga qo‘shilganini va tarmoqqa ulanganini tekshiring.

t the Zigbee gateway is
dded to the Wi-Fi
he app before adding the

ULANISH REJIMI

4. Elektrik montajni tugatganidan so‘ng Reset tugmasini taxminan 10 soniya bosib turing.

Indikator tez miltillaganda modul ulanishga tayyor

ndicator is blinking
ed, the gateway is
er switch power on/off 5
t the indicator is blinking

QO‘SHIMCHA QURILMA QO‘SHISH

5. Shlyuz boshqaruv oynasida “+ / Add sub-device” tugmasini tanlang.

Ilovadagi ko‘rsatmalarga amal qiling.



xy control panel, choose
‹device" and follow the
structions.

ULANISH JARAYONI

6. Qurilma qidirilishini kuting. Ulanish odatda 10–120 soniya davom etadi.


Davomiylik tarmoq sharoitiga bog‘liq.

the gateway discovers the
nnection typically takes
120 seconds depending on
ork conditions.

QURILMA TAYYOR

7. Ulanish tugagach, modul ilovada paydo bo‘ladi.

8. Endi uni telefoningizdan boshqarishingiz mumkin.



ne / iPad (iOS 7.0 or higher)
ge 4.0 or higher

M REQUIREMENTS

router
e gateway
phone
figuration is done, the Zigbee
ice will be shown in the
ge list.

ly, you can control the
via your mobile phone.